

www.FGWilson.com

# P110-2



Image for illustration purposes only.

Output Ratings		
Generating Set Mo	del Prime*	Standby*
380-415V,50Hz	100.0 kVA / 80.0 kW	110.0 kVA / 88.0 kW
480V, 60 Hz	113.0 kVA / 90.4 kW	125.0 kVA / 100.0 kW

Ratings at 0.8 power factor.

### **Prime Rating**

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.


#### Standby Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

# **Standard Reference Conditions**

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m (328 ft) A.S.L. 30% relative humidity.

Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998, Class A2.



Ratings and Performance Data			
Engine Make & Model:		Perkins 1104C-4	14TAG2
Alternator manufactured for FG Wilson by:		Leroy Somer	
Alternator Model:	l	LL3014B	
Control Panel:		PowerWizard 1.	1
Base Frame:	ļ	Fbc2 - (08Hr)	
Circuit Breaker Type:	;	3 Pole MCCB	
Frequency:		50 Hz	60 Hz
Engine Speed: RPM		1500	1800
Fuel Tank Capacity: litres (US gal)		250 (66.0)	
Fuel Consumption: I/hr (US gal/hr)			
(100% Load)	Prime	21.9 (5.8)	26.3 (6.9)
	Standby	24.1 (6.4)	29.3 (7.7)

## **Available Options**

- CE Certification
- Sound Attenuated EC Enclosures
- Control Panel Upgrades
- Range of Silencers
- Range of Remote Fuel Systems
- Range of Alarms and Shutdowns

Dimensions ar	nd Weights			
Length (L) mm (in)	Width (W) mm (in)	Height (H) mm (in)	<b>Dry</b> kg (lb)	<b>Wet</b> kg (lb)
2089 (82.2)	1120 (44.1)	1367 (53.8)	1182 (2607)	1200 (2646)
Dry = With Lube	Oil	Wet = With Lube	e Oil and Coolant	

Ratings in accordance with ISO 8528, ISO 3046, IEC 60034, BS5000 and NEMA MG-1/22. Generating set pictured may include optional accessories.

## FG Wilson has manufacturing facilities in the following locations:

Northern Ireland • Brazil • China • India • USA

With headquarters in Northern Ireland, FG Wilson operates through a Global Dealer Network. To contact your local Sales Office please visit the FG Wilson website at www.FGWilson.com

Engine Technical Data	
No. of Cylinders / Alignment:	4 / In Line
Cycle:	4 Stroke
Bore / Stroke: mm (in)	105.0 (4.1)/127.0 (5.0)
Induction:	Turbocharged Air To Air Charge Cooled
Cooling Method:	Water
Governing Type:	Electronic
Governing Class:	ISO 8528 G2
Compression Ration:	18.3:1
Displacement: I (cu. in)	4.4 (268.5)
Moment of Inertia: kg m2 (lb/in2)	1.51 (5160)
Engine Electrical System:	
- Voltage / Ground	12/Negative
- Battery Charger Amps	65
Weight: kg (lb) - Dry	500 (1102)
- We	520 (1146)

Performance	5	0 Hz	60 Hz
Engine Speed: rpm	1	1500	1800
Gross Engine Power: kW (hp)			
- Prir	ne 93.6	(126.0)	106.8 (143.0)
- Stand	by 103.0	0 (138.0)	117.5 (158.0)
BMEP: kPa (psi)			
- Prir	ne 1702.	.0 (246.9)	1619.0 (234.8)
- Stand	by 1873.	0 (271.7)	1781.0 (258.3)

Fual	·c.	rata ma
ruei	-51	/stem

Fuel Filter Type: Replaceable Element
Recommended Fuel: Class A2 Diesel

Fuel Consumption: I/hr (US gal/hr)

	110%	100%	75%	50%
Prime	Load	Load	Load	Load
50 Hz	24.1 (6.4)	21.9 (5.8)	16.6 (4.4)	11.7 (3.1)
60 Hz	29.3 (7.7)	26.3 (6.9)	19.9 (5.3)	14.2 (3.8)

	110%	100%	75%	50%
Standby	Load	Load	Load	Load
50 Hz		24.1 (6.4)	18.2 (4.8)	12.6 (3.3)
60 Hz		29.3 (7.7)	21.9 (5.8)	15.4 (4.1)

(Based on diesel fuel with a specific gravity of 0.84 and conforming to BS2869, Class A2)  $\,$ 

Air Systems		50 Hz	60 Hz
Air Filter Type:		Replaceab	le Element
Combustion Air Flow: m3/min	(cfm)		
	- Prime	6.0 (212)	7.8 (274)
	- Standby	6.3 (221)	7.8 (275)
Max. Combustion Air Intate		(/	(=, 0)
Restriction: kPa (in H <sub>2</sub> O)		8.0 (32.1)	8.0 (32.1)

Cooling System		50 Hz	60 Hz
Cooling System Capacity: I (US go	al)	17.5 (4.6)	17.5 (4.6)
Water Pump Type:		Centr	rifugal
Heat Rejected to Water & Lube	Oil:		
kW (Btu/min)	- Prime	46.1 (2622)	57.7 (3281)
-	Standby	50.7 (2883)	64.0 (3640)
Heat Radiation to Room: Heat ro	diated from e	engine and alternator	
kW (Btu/min)	- Prime	6.8 (387)	8.5 (483)
-	Standby	7.5 (427)	9.4 (535)
Radiator Fan Load: kW (hp)		2.8 (3.8)	4.8 (6.4)
Radiator Cooling Airflow: m3/min	(cfm)	187.8 (6632)	244.2 (8624)
External Restriction to Cooling Airflow: Pa (in H <sub>2</sub> O)		125 (0.5)	125 (0.5)

Lubrication System	
Oil Filter Type:	Spin-On, Full Flow
Total Oil Capacity: I (US gal)	8.0 (2.1)
Oil Pan: I (US gal)	7.0 (1.8)
Oil Type:	API CC/SE
Oil Cooling Method:	Water

Cooling system designed to operate in ambient conditions up to  $50^{\circ}$ C ( $122^{\circ}$ F). Contact your local FG Wilson Dealer for power ratings at specific site conditions.

Exhaust System	50 Hz	60 Hz
Silencer Type:	Indu	ıstrial
Silencer Model & Quantity:	SD5	0 (1)
Pressure Drop Across Silencer System: kPa (in Hg)	2.10 (0.620)	3.56 (1.051)
Silencer Noise Reduction Level: dB	22	17
	18.0 (5.3)	15.0 (4.4)
Exhaust Gas Flow: m3/min (cfm)		
- Prime	15.2 (537)	18.4 (650)
- Standby	16.3 (576)	20.4 (720)
Exhaust Gas Temperature: °C (°F)		
- Prime	514 (957)	517 (963)
- Standby	543 (1009)	574 (1065)

Alternator Physical Data	
Manufactured for FG Wilson by:	Leroy Somer
Model:	LL3014B
No. of Bearings:	1
Insulation Class:	н
Winding Pitch Code:	2/3 - 6
Wires:	12
Ingress Protection Rating:	IP23
Excitation System:	Shunt
AVR Model:	R250

Alternator Operating Data	
Overspeed: rpm	2250
Voltage Reguation: (Steady state)	+/- 0.5
Wave Form NEMA = TIF:	50
Wave Form IEC = THF:	2.0%
Total Harmonic content LL/LN:	4.0%
Radio Interference:	Suppression is in line with European Standard EN61000-6
Radiant Heat: kW (Btu/min)	
- 50 Hz	9.0 (512)
- 60 Hz	11.0 (626)

Alternator Performance Data:	50 Hz			60 Hz					
Data Item	415/240V	400/230V 230/115V 200/115V	380/220V 220/110V	220/127V	480/277V 240/139V	380/220V 220/110V	240/120V 208/120V	230/115V	440/254V 220/127V
Motor Starting Capability* kVA	187	176	160	208	206	136	160	149	177
Short Circuit Capacity** %	300	300	300	300	300	300	300	300	300
Reactances: Per Unit									
Xd	3.200	3.440	3.810	2.840	3.240	5.080	4.310	4.660	3.850
X'd	0.120	0.130	0.150	0.110	0.130	0.200	0.170	0.180	0.150
X"d	0.074	0.080	0.089	0.066	0.075	0.118	0.100	0.108	0.090

Reactances shown are applicable to prime ratings.

\*Based on 30% voltage dip at 0.6 power factor.

\*\*With optional permanent magnet generator or AREP excitation.

· ·	nical Data 50 F		Ctondhu		
Voltage	Prii	ne:	Standby:		
	kVA	kW	kVA	kW	
415/240V	100.0	80.0	110.0	88.0	
400/230V	100.0	80.0	110.0	88.0	
380/220V	100.0	80.0	110.0	88.0	
230/115V	100.0	80.0	110.0	88.0	
220/127V	100.0	80.0	110.0	88.0	
220/110V	100.0	80.0	110.0	88.0	
200/115V	100.0	80.0	110.0	88.0	

Voltage Technical Data 60 Hz					
Voltage	Priı	me:	Standby:		
	kVA	kW	kVA	kW	
480/277V	113.0	90.4	125.0	100.0	
220/127V	113.0	90.4	125.0	100.0	
380/220V	111.0	88.8	122.0	97.6	
240/120V	113.0	90.4	125.0	100.0	
230/115V	113.0	90.4	125.0	100.0	
440/254V	113.0	90.4	125.0	100.0	
220/110V	111.0	88.8	122.0	97.6	
208/120V	113.0	90.4	125.0	100.0	
240/139V	113.0	90.4	125.0	100.0	

Documentation
A full set of operation and maintenance manuals and circuit wiring diagrams.
Generating Set Standards
The equipment meets the following standards: BS5000, ISO 8528, ISO 3046, IEC 60034, NEMA MG-1.22.
FG Wilson is a fully accredited ISO 9001 company.  EU Stage II Emissions Compliant.
LO Stage ii Emissions Compilant.
Warranty
All prime equipment carries a one year manufacturer's warranty. Standby equipment, limited to 500 running hours per year, has a two year manufacturer's
warranty. For details on warranty cover please contact your local Dealer, or visit our website: FGWilson.com.
Dealer contest dataile
Dealer contact details:

FG Wilson has manufacturing facilities in the following locations:

Northern Ireland • Brazil • China • India • USA

**General Information** 

With headquarters in Northern Ireland, FG Wilson operates through a Global Dealer Network.

To contact your local Sales Office please visit the FG Wilson website at www.FGWilson.com